

## How to use custom graphics with the new V05.00.xx 'Full Screen' ATM software

The new 'Full Screen' ATM software uses screen panels that fill up the entire screen to maximize the visual impact and make full use of the LCD panel. This required changes as to how advertisements are made and uploaded to the ATM. The following will explain what you need to know to manage your custom graphics.

### Creating new custom ads:

The main difference with creating ads for the new software is the image dimensions and the files are now stored as JPG (JPEG) images rather than BMP (Bitmap).

Wide-screen ATMs (1700W/G1900/G2500/G3500/GT3000), the new size is 800x480 pixels.


10.4" 'square' screen ATMs (C4000/T4000), the new size is 800x600 pixels

Screens larger than 10.4", (GT5000/G6000) the size is 1024x768

Onyx ATM the size is 1280x800 pixels

File naming is the same as before, however make sure to save the images as JPG.

For example center1.jpg, center2.jpg



When planning your graphics, note that if you use 'Welcome' text, it will appear overlaid onto the custom image (see above 'NEW SOFTWARE') so either plan on that when creating your custom image, or you can delete the text from the Welcome Message.


For advanced users, you can still modify the 'Welcome Screen' as center0.jpg

### Upgrading an existing machine:

If you install the new V05 software as an 'Update' to your existing ATM, the 'update' version of the software will not delete any custom ad screens you may have installed.

Note: For advanced users, the card logo screen and the 'center0.bmp' files are no longer used. If you have created custom card logos or custom Welcome screen, they will be overwritten when you update to the new software.

If you did not have any custom graphics, then you will only see the new 'Full Screen' graphics. However if you do, then the old graphics (center1 through center8) will now show up in the middle of the screen as shown in the example below:



Note the yellow text above the graphic ("NEW SOFTWARE") which is the 'Welcome' text message entered through the Operator Menu. Customer Setup → Change Message.

### Full Software Install on existing machine:

If you do a 'Full Install' of software, as with previous versions you will wipe out any custom ads on the ATM. In this case you will only see the new default graphics included with the new software.

### Deleting old ads:

If you have custom ads on your ATM and after doing an 'Update', you would like to delete them and use the new default ads, there is a new option in the menu to allow you to delete any older ads without having to do a Full Install. Go to Operator Menu → Customer Setup → Screen Graphics and you'll see a button to 'Clear Adver. BMP'





This will delete any custom BMP files stored in the ATM. At that point you will only then see the default Full Screen ads until you load new custom ads.



### Deleting new custom ads:

As with the previous ATM software, if you want to change any ad, you must overwrite it with a new file. If at any point you'd like to return to the default ads, you'll need to do a Full Install of software.

If you have any questions not covered here, please contact Technical Support for assistance.